

Joyful Life P6321 Home Entertainment Small Music System



In/Outputs	Input Source	Two sets of stereo audio input: 2.0 (L、R), 2.1 (L、R、SUB) Users can freely switch the current effective audio source.
	Audio input connectors	RCA connector
	HF output power (8Ω)	2x 30W
	MF output power (8Ω)	2x 30W
	Sub output power (8Ω)	160W
	Audio output connectors	3 sets of Phoenix connector: L (LH、LM), R (RH、RM), EXT SUB
	5V output connectors (EXT LED 5V)	3.5mm connector
	Power supply	220-240V ~ 50-60Hz
Nominal Parameters	Components	1x 6.5" LF driver Using B&C excellent drivers
	Audio processing	Built-in DSP; Support FIR phase correction technology.
	Input resistance	10KΩ (Unbalanced)
	THD	<0.1%
Protection	DC protection	0.7-1V
	Short-circuit protection	Yes
	Overheat protection	Yes
Dimension	WxHxD	194 x 290 x 445 mm
	Net Weight	11kg

Technical Parameter of HF cube loudspeaker

In/Outputs	Input connectors	Snap-in connector
Nominal Parameters	Component	1x 0.75" throat 1" voice coil LF driver Using B&C excellent drivers
	Coverage	90° Hor X 60° Ver
	Audio processing	Support FIR phase correction technology. (Need to be used with active subwoofer with built-in DSP)
Dimension& Weight	WxHxD	102 x 95 x 108 mm
	Net Weight	0.55kg

Technical Parameter of MF cube loudspeaker

In/Outputs	Input connectors	Snap-in connector
Nominal Parameters	Component	1x 3.5" full range driver Using B&C excellent drivers
	Coverage	120° round coverage angle
	Audio processing	Support FIR phase correction technology. (Need to be used with active subwoofer with built-in DSP)
Dimension& Weight	WxHxD	102 x 95 x 108 mm
	Net Weight	0.45kg