







Full Range Loudspeaker

- Sompact in size, easy to hide
- High power handling capacity





Technical Specifications:

Technical Parameters	S35F
Frequency Response	160Hz-18KHz±3dB
Coverage	Hor: 90°, Ver: 60°
Components	1×0.75 inch HF driver 4×3.5 inch full-range driver
Recommended Amplifier	120W-240W
Nominal Impedance	8Ω
Sensitivity (1W/1M)	93dB
Max. SPL	120dB
Installation	Bracket Seat on the bottom, Flying Nuts onthe back
Connectors	2x NEUTRIK NL-4
Dimension (H×W×D)	576mm×99mm×134mm
Weight	4Kg